



KF40D5

SILENT DIESEL GENERATOR

400V / 50Hz 3 PHASE

• GENSET POWER

Prime Power	40 KVA / 32 KW
Standby Power	44 KVA / 35.2 KW

• GENERAL INFORMATION

Engine	Fawde
Alternator	Koten
Controller	Smartgen
Governor	Electronic
Frequency	50Hz
Phase	3Ph
Power factor	0.8
Fuel tank capacity	8hrs
Engine start voltage	12V
Noise Level	72dBA

• ENGINE

Brand	FAWDE
Model	4DX21-53D
Fuel injection system	Direct Inject diesel
No. of cylinders	4
Bore	102mm
Stroke	118mm
Compression ratio	17:1
Displacement	2.54L
Engine speed	1500 RPM
Rated power	39KW

• ALTERNATOR

Brand	Koten
Model	KA-184J
Insulation type	Class 'H'
Winding Pitch	2/3
Voltage regulation	±0.5



CONTROLLER
Smartgen 6120

VOLTAGE OPTIONAL

220 / 380 V
230 / 400V
240 / 415 V

DIMENSION SILENT

Length (L)	2200 mm
Width (W)	900 mm
Height (H)	1150 mm
Weight	930 KG

FUEL CONSUMPTION 1500RPM (L/HR)

100% Prime power	8.93 L/hr
75% Prime power	7.05 L/hr
50% Prime power	5.26 L/hr

Genset Optional

- Genset Color
- Engine water pre-heater
- Daily fuel tank
- ATS
- ComAp/Deepsea Controller

Quality Standards

- ISO9001:2000
- ISO8528 BS4999
- BS5514,AS1359,
- ICE34 CE Compliance

Warranty

- 1 Year

Fuzhou Koten Power Equipment Co.,Ltd.
Fuzhou,China.
www.kotenpower.com
Tel: +8613705003748,+8615960024397